

VI.3.6B-SETUP-USER SETUP: U - USER CONTROLS AND OPTIONS MENU

Information controlled by this menu is used by the Product Generation application. The menu appears as:

USER CONTROLS MENU	
Guidance Product file(s) ([0]-Many 1-Single):	(1) 0
Comms System ([1]-AWIPS 2-AFOS	(2) 1
FFG Physical elements ([1]-PF 2-PP):	(3) 1
Year Format ([4]-ccyy 2-yy):	(4) 4
Append Name ([0]-No 1-Office 2-Fcstr 3-Both):	(5) 0
Select (1-5 or <return>-exit):	

The values appearing in square brackets are the default values.

SHEF products are written to file(s) according to the value of (1) above:

- 0 = one product per file resulting in many files, or
- 1 = all products are concatenated into a single file

The Communication System (2) selected determines the format of the communications header at the beginning of the products.

FFG Physical elements (3) controls the SHEF physical element code for Flash Flood Guidance:

- 1 = PFd
- 2 = PPdCF

where d is the duration code

The office phone number and duty forecaster are appended to each SHEF product when item (4) above is set to 1, 2 or 3. To edit the duty forecaster list, reset item (4) to 1, 2 or 3 and follow the prompts.

Enter control (0, 1, 2 or 3): 3

Enter parameters (f-file [t]-terminal m-menu):

Selection f

Input duty forecasters and phones from a file:

Enter path and/or filename:

Selection t

EDIT DUTY FORECASTERS		
1	office	918-123-4567
2	abc	forecaster 1
3	def	forecaster 2
	.	
	.	
20	xyz	forecaster 20
Select (a-add c-change d-delete <return>-exit:		
Enter line # (0-exit):		

Office is the key word to identify the office phone number. Symbols abc, def and xyz represent forecasters' initials. Symbols can be up to 8 characters.

Selection m

This selection returns to the previous menu, the Setup Menu.